



Ejemplo: Filtro Pasa Bajos Chebyshev Banda de 80m con valores normalizados de capacidad

Banda	Frec. corte	ROE	C1 y C7 (pF)	C3 y C5 (pF)	L2 y L6 (uH)	L4 (uH)
160m	2.02 MHz	1.09	1200	2700	5.42	6.41
80m	4.11 MHz	1.07	560	1300	2.62	3.13
40m	7.98 MHz	1.08	300	680	1.37	1.62
30m	10.37 MHz	1.14	270	560	1.09	1.26
20m	15.16 MHz	1.09	160	360	0.72	0.85
15m	21.69 MHz	1.06	100	240	0.49	0.59
10m	36.85 MHz	1.10	68	150	0.30	0.36